

## 15TOPV8RGBW

### Control unit dimmer TOP-V8/RGBW for led RGB and RGBW CV 12-24-36V

January 07th, 2025, 03:01



## DESCRIPTION

Receiving control unit with dimmer function for control, via radio 433.92MHz or with cable via standard pushbutton, of led power supplies at constant voltage of 12, 24V or 36VDC. For RGB and RGBW led strips. Maximum intensity per 8A output with a maximum total of 24A. Possibility to connect up to 4 slaves (extend) allowing to synchronize high powers. With 3 cable entries for standard push buttons. Wide and precise regulation and gradual rise and fall time (FADE) adjustable from 0 to 10 seconds. Simple programming through display. Its reduced dimensions allow its installation in the false ceiling or junction boxes.

## PRICE

| Lot | P.V.P. excluding VAT |
|-----|----------------------|
| 1   | 98,25€               |
| 10  | 93,57€               |

Continued on next page >>

SMART LIGHTING > Lighting control by Nexta Tech > Receivers  
Constant voltage control, Dimmer, RGBW, CCT, DTW

## 15TOPV8RGBW

Control unit dimmer TOP-V8/RGBW for led RGB and RGBW CV 12-24-36V

### TECHNICAL SPECIFICATIONS

---

#### SYMBOLS



#### CERTIFICADOS



Weight: 220 Grams

### NOTES

---

Dimmer for LEDs with constant voltage 12-24-36 Vdc of RGB and RGBW LEDs. 4 outputs max 8A per output (max 24A total) With 3 cable entries and input to extend

### OTHER FEATURES

---

Length (mm): 174

Width (mm): 46

High (mm): 35

Voltage In (Vdc): 12~36

Room Temperature (°C): -20~+55

Ingress Protection: IP20

### DOCUMENTS

---

 [Data Sheet](#)

 [Quick start guide](#)

 [Mounting instructions](#)

 [CE](#)