

SMART LIGHTING > Lighting control by Nexta Tech > Receivers Driver control 0-1/10V, dali, Push dim or phase cut

## 15TOP0110

# Control unit interface TOP-0110 for drivers 0-1/10V 2000W



## DESCRIPTION

Interface control unit with dimmer function for wireless control via 433.92MHZ radio or with standard push button cable of devices with 0-10V or 1-10V input. Power 110-240Vac. Output 0-10V / 1-10V Maximum power 2000W (240Vac) The programming by display is intuitive and fast while its small dimensions allow for installation in the false ceiling or junction boxes.

#### PRICE

Lot	P.V.P. excluding VAT
1	86,68€
10	82,55€

Continued on next page >>



SMART LIGHTING > Lighting control by Nexta Tech > Receivers Driver control 0-1/10V, dali, Push dim or phase cut

## 15TOP0110

Control unit interface TOP-0110 for drivers 0-1/10V 2000W

## **TECHNICAL SPECIFICATIONS**

#### SYMBOLS

CERTIFICADOS





CE

Weight: 227 Grams

### NOTES

Receiver for RF regulation or cable of devices with input 0-1 / 10V max 2000W

### **OTHER FEATURES**

Length (mm): 174 High (mm): 35 Power (W): 2000

Ingress Protection: IP20

Width (mm): 46 Voltage In (Vac): 110~240 Room Temperature (°C): -20~+55

#### DOCUMENTS

- Data Sheet
- Quick start guide
- Mounting instructions