

G50542502N - 039982

Dimmer Led pushbutton and cursor 1012 / S LFP SW1A 100-240V 250W black

July 03rd, 2024, 05:22



arditi
LIGHTING INNOVATION

DESCRIPTION

Universal table or floor regulator for incandescent and dimmable LED bulbs.
Continuous regulation to the minimum light. Equipped with additional electronic protection for the end of lamp life. For flat and round hose cables. Provided with ground terminal.
The LFP (Load Fallilure Protection) electronic protection consists of special built-in electronics that perform a double function:
1)In the hypothetical case that at the end of the bulb's life it was short-circuited, an overload would occur and then the dimmer would be protected and stop working, but simply by disconnecting from the mains and reconnecting the dimmer it would be operational again . Dimmers that do not have this special electronics are protected and disconnected in case of overload but do not work again.
2) The possibility of setting the minimum regulation desired. This allows you to adjust a higher minimum level if the bulb flickers and thus prevent the lamp from flickering. The instructions that accompany the product indicate how to adjust the minimum configuration.

PRICE

Lot	P.V.P. excluding VAT
1	26,17€
5	23,79€
10	21,65€
40	20,64€



LED TECHNOLOGY > Electronic Led Power Supplies > Led Controllers
Dimmer Led 230V

G50542502N - 039982

Dimmer Led pushbutton and cursor 1012 / S LFP SW1A 100-240V 250W black

TECHNICAL SPECIFICATIONS

SYMBOLS



CERTIFICADOS



Weight: 94 Grams

Packging: Box 40 Units

NOTES

Type de charge: Incandescence 4-250W (220-240V), 4-200W (120V)

OTHER FEATURES

High (mm): 29

Diameter (mm): 100

Colour: Black

Voltage In (Vac): 100~240

Frecuency (Hz): 50~60

Power (W): 4~25

Room Temperature (°C): +35

DOCUMENTS

 [Data Sheet](#)

 [Mounting instructions](#)

 [Dimmer Led pushbutton and cursor 1012 / S LFP SW1A 100-240V 250W black](#)

DIMMER 1012/S/AS

 [CE](#)

 [ENEC \(Italy\)](#)

 [UKCA](#)

 [UR \(USA\)](#)