

G507201

Electronic relay HZK201 with touch sensor

November 03rd, 2024, 12:30



DESCRIPTION

Class II electronic sensory relay, power 500W, adjustable touch sensitivity, maximum 4 meters for effectiveness of the touch cable, operation 1 touch turns on, another touch turns off. This power supply complies with The European Low Voltage Directive LVD 2006/95/EC and complies with the European Electromagnetic Compatibility Directive EMC 2004/108/EC.

The HZK201 contact sensor model is designed exclusively for use in lighting elements (incandescent, halogen, LED, fluorescent lamps, with or without transformer). The luminaires will be turned on or off with a simple contact on the active part of the sensor. Be sure Make sure the device is installed correctly, as shown in the instruction diagram.

The contact sensor is factory configured with a medium sensitivity standard. The user can regulate this sensitivity by turning the regulator located on the side of the sensor and as indicated on the sensor box. The length of the sensor cable should not exceed 4 meters. If the cable is damaged, it must be replaced by qualified personnel.

If the luminaire in which the sensor has been installed turns on and off automatically on its own, without contact with the sensor (the sensitivity is too high), turn the regulator in the direction (-), until the luminaire goes off. Turn off with normal use of the sensor (tap gently)

If the luminaire in which the sensor has been installed only works with a strong touch (the sensitivity is too low or non-existent), turn the dimmer in the direction of (+), until the luminaire turns on and off with a light touch . in the sensor The sensor cable must be installed as short as possible and as close as possible to the manual contact area, always in direct contact with the metal part, if the metal part is excessively insulated (paint or other type of surface finishes, insulators) the sensor may not work properly

PRICE

Copyright © 2024 Koala Components, S.A. All rights reserved.

P.V.P. excluding VAT

Lot

1

15,37€

5

14,34€

G507201

Electronic relay HZK201 with touch sensor

TECHNICAL SPECIFICATIONS

SYMBOLS



CERTIFICADOS



Weight: 39 Grams

Packging: Box 1 Unit

NOTES

Adjustable touch sensitivity. Maximum 4 meters touch control cable.

OTHER FEATURES

Length (mm): 106

Width (mm): 32

High (mm): 21

Voltage In (Vac): 220~240

Voltage Out (Vac): 220~240

Frecuency (Hz): 50

Power (W): 500

Temperature (°C): 80

Ingress Protection: IP20

DOCUMENTS

 [Data Sheet](#)

 [Mounting instructions](#)

 [Electronic relay HZK201 with touch sensor](#)

 [CE](#)