

A413980

Led power supply CC Minibravo RN1398 350-500-700mA 14-20-22W

December 04th, 2024, 09:14



DESCRIPTION

Alimentador Led para uso independiente con salida a corriente constante 350mA (14W) -500mA(20W) -700mA (22W) seleccionable con jumper. Para 1 a 10 Led conectados en serie. Clase II. Protección térmica, sobrecarga, sobretension y cortocircuito. Se debe encender y apagar desde el primario. Dimensiones muy reducidas y compactas. Agujero central de 10mm de diametro

PRICE

Lot	P.V.P. excluding VAT
1	23,99€
5	18,45€
10	17,65€
40	17,16€



Continued on next page >>

A413980

Led power supply CC Minibravo RN1398 350-500-700mA 14-20-22W

TECHNICAL SPECIFICATIONS

SYMBOLS

SELV



CERTIFICADOS



Weight: 0 Grams

Packging: Box 40 Units

NOTES

Output to constant current 350mA (15W) -500mA (20W) -700mA (22W) selectable with jumper.

OTHER FEATURES

High (mm): 24

Diameter (mm): 72

Voltage In (Vac): 220~240

Voltage Out (Vdc): 48

Intensidad Out (A): 0.35~0.7

Frecuency (Hz): 50~60

Power (W): 14~22

Room Temperature (°C): -20~+40

Critical Temperature (°C): 80

Ingress Protection: IP20

Power factor: 0.57

DOCUMENTS

 [Data Sheet](#)

 [Mounting instructions](#)

 [Led power supply CC Minibravo RN1398 350-500-700mA 14-20-22W](#)